## MSI 880GMS-E35 motherboard AMD 880G Socket AM3 micro ATX

Brand: MSI Article code: 880GMS-E35

**Product name:** 880GMS-E35

880GMS-E35, AMD AM3 CPU, AMD 880G/SB850, 2  $\times$  DIMM DDR3, 6  $\times$  SATA 6.0Gbps, 7.1ch. HDA, Gigabit Lan, D-Sub, DVI-D, HDMI, Micro ATX

MSI 880GMS-E35. Processor manufacturer: AMD, Processor socket: Socket AM3, Compatible processor series: AMD Phenom II X2, AMD Phenom II X4, AMD Phenom II X6. Maximum internal memory: 16 GB, Memory channels: Dual-channel, Memory voltage: 1.5 V. RAID levels: 0, 1, 10, JBOD. Ethernet interface type: Gigabit Ethernet, LAN controller: Realtek RTL8111E. Component for: PC, Motherboard form factor: micro ATX, Motherboard chipset: AMD 880G





| Processor                                       |  | Internal I/O                             |                                   |
|---|--|--|-----------------------------------|
| Processor manufacturer *                        | AMD  | TPM connector                            | ✓                                 |
| Processor socket *                              | Socket AM3 Rear                                      | Rear panel I/O ports                     |                                   |
| Compatible processor series *                   | AMD Phenom II X2, AMD Phenom II X4, AMD Phenom II X6 | USB 2.0 ports quantity *                 | 6                                 |
| Maximum number of SMP                           | 1  | Ethernet LAN (RJ-45) ports *             | 1                                 |
| processors                                      | 1  | PS/2 ports quantity                      | 1                                 |
| Memory  |  | VGA (D-Sub) ports quantity *             | 1                                 |
| Number of memory slots *                        | 2  | HDMI ports quantity *                    | 1                                 |
| Memory channels                                 | Dual-channel   | DVI-D ports quantity * Headphone outputs | 1                                 |
| Memory voltage                                  | 1.5 V  | Microphone in                            | <b>∠</b>                          |
| ECC compatibility Supported memory clock speeds | Non-ECC<br>800,1066,1333 MHz                         | ,  | •                                 |
| Maximum internal memory *                       | 16 GB  | Network                                  |                                   |
|   | 10 05  | Ethernet interface type  LAN controller  | Gigabit Ethernet Realtek RTL8111E |
| Storage controllers                             | 0.1.10.1000  |  | Rediter RILBITTE                  |
| RAID levels                                     | 0, 1, 10, JBOD                                       | Features                                 |                                   |
| Graphics  |  | Motherboard chipset *                    | AMD 880G                          |
| Parallel processing technology support *        | Not supported  | Motherboard southbridge<br>Audio chip    | AMD SB850<br>Realtek ALC887       |
| On-board graphics card                          | ✓  | Audio output channels *                  | 7.1 channels                      |
| Internal I/O                                    |  | Component for *                          | PC                                |
| USB 2.0 connectors *                            | 3  | Motherboard form factor *                | micro ATX                         |
| Number of SATA III connectors *                 | 6  | Power source type                        | ATX                               |
| S/PDIF out connector                            | ✓  | Expansion slots                          |                                   |
| Front panel audio connector                     | ✓  | PCI Express x1 slots                     | 1                                 |
| ATX Power connector (24-pin)                    | ✓  | PCI Express x16 slots PCI slots          | 1                                 |
| CPU fan connector                               | ✓  | PCI SIOTS PCI Express slots version      | 2.0                               |
| Number of chassis fan connectors                | 1  | •  |                                   |
| Chassis intrusion connector                     | ✓  | Weight & dimensions                      | 0.6111/0.44                       |
| Peripheral (Molex) power connectors (4-pin)     | 1  | Width<br>Depth                           | 9.61" (244 mm)<br>8.07" (205 mm)  |
|   |  |  |                                   |

| Packaging content         |           |  |
|---------------------------|-----------|--|
| Drivers included          | ✓         |  |
| Other features            |           |  |
| Controller interface type | AMD SB850 |  |

## **Catalog Object Cloud**



Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.